



MAGNATECH LED
Simply Brilliant

SOXLED

LED replacement for LPS Lamps



Magnatech LED have designed and developed a unique direct LED replacement for the 35W, 55W and 90W SOX lamps and with similar dimensions to the original SOX bulb thus allowing for trouble-free retro-fit.

By simply removing the ballast and fitting our SOXLED bulb into the existing head you benefit from lower power consumption, long life and therefore lower maintenance costs. There is also the added advantage of a high CRI giving a much better quality of light.

The extruded aluminium heatsink ensures adequate cooling when used in enclosed fittings.

Features

- ✓ Rotating base
- ✓ Internal driver
- ✓ B22 Base

Replaces

- ✓ 16W replaces 35W
- ✓ 18W/24W replaces 55W
- ✓ 28W replaces 90W

Applications

- ✓ Private roads
- ✓ Industrial areas
- ✓ Highways

Model	SL07 16W	SL08 18W	SL08 24W	SL09 28W
Power	16W	18W	24W	28W
Light Output (Lm)	>1600	>1800	>2400	>2800
Dimension mm	310*54Ø	425*54Ø	425*54Ø	528*54Ø
Input Voltage	85-265V AC 50/60Hz			
Beam Angle	140*80°			
CRI	>70			
IP Grade	IP40			
Colours	3000K, 4500K, 6000K			

Details subject to change without notice

European Headquarters.

Magnatech LED (UK) Ltd.

Magna House
Dales Manor Business Park
Cambridge CB22 3TJ. U.K.
Tel: +44 (0)1223 834800
Email: sales@magnatechled.co.uk

Global Sales and Manufacturing

Huizhou Magnatech LED

4th Floor, Building A, Tianhao Industrial Park
Zhongkai Hi-Tech Industrial Area
Huizhou City, GuangDong, China
Tel: +86 (0) 752 5707 468
Email: info@magnatechled.com

www.magnatechled.com