

# eXalite

## T8 LED tube.



The Magnatech LED eXalite series of LED T8 fluorescent tube replacements are the ultimate in performance.

Using the latest generation of LED chips, the eXalite series offers exceptional performance and reliability.

Available as standard with over 100Lm/W and Prime with efficiency of more than 140Lm/W.

The eXalite series uses single-end power and rotating end-caps as standard ensuring compatibility with all types of fittings. Fitting is complete by simply inserting the eXalite tube and replacing the starter with the fused link supplied. For electronic ballast the fitting will need to be re-wired. Full fitting instructions are supplied.

### Features

- ✓ Aluminium and plastic
- ✓ Rotating caps
- ✓ High efficiency

### Replaces

- ✓ T8 fluorescent tubes
- ✓ 600mm to 2400mm
- ✓ 18W to 70W tubes

### Applications

- ✓ Hotels
- ✓ Shops
- ✓ Offices

Model		eXalite T8					
Dimension	mm	590*26mm	895*26	1199*26	1500*26	1764*26	2375*26
Power		9W	14W	18W	24W	28W	36W
Light Output	Standard	900Lm	1400Lm	1800Lm	2400Lm	2800Lm	3600Lm
	Prime	1260Lm	1960Lm	2520Lm	3360Lm	3920Lm	5040Lm
Input Voltage		85-265V AC 50/60Hz					
Beam Angle		120°					
CRI		>80					
IP Grade		IP40					
Colours		3000K, 4000K, 6000K					

Details subject to change without notice

### European Headquarters.

#### Magnatech LED (UK) Ltd.

Magna House  
Dales Manor Business Park  
Cambridge CB22 3TJ. U.K.  
Tel: +44 (0)1223 834800  
Email: sales@magnatechled.co.uk

### Global Sales and Manufacturing

#### Huizhou Magnatech LED

4<sup>th</sup> Floor, Building A, Tianhao Industrial Park  
Zhongkai Hi-Tech Industrial Area  
Huizhou City, GuangDong, China  
Tel: +86 (0) 752 5707 468  
Email: info@magnatechled.com