

eXalite-Five

LED replacement for T5 Tubes



The Magnatech eXalite-Five series of LED T5 fluorescent tube replacements utilize the latest generation of high output LED chips to offer superior light output.

Consuming only around 50% of the energy of a standard fluorescent tube, the eXalite-five is designed to replace standard T5 fluorescent tubes.

With efficiency of 140Lm/W they offer superior brightness and light quality than most standard T5 fluorescents.

Using an external driver, the eXalite-five is available with 0-10V, DALI and push-dim drivers as options.

Features

- ✓ Aluminium and plastic
- ✓ External driver
- ✓ 140Lm/W

Replaces

- ✓ 600mm to 1500mm T5
- ✓ 18W to 54W tubes

Applications

- ✓ Hotels
- ✓ Shops
- ✓ Offices

Model	eXalite-Five			
Dimensions	549*16mm	848*16mm	1149*16mm	1449*16mm
Power	9W	14W	18W	24W
Light Output	1260Lm	1960Lm	2520Lm	3360Lm
Input Voltage	85-265V AC 50/60Hz			
Beam Angle	120°			
CRI	>80			
IP Grade	IP40			
Colours	3000K, 4000K, 6000K			

Details subject to change without notice

European Headquarters.

Magnatech LED (UK) Ltd.

Magna House
Dales Manor Business Park
Cambridge CB22 3TJ. U.K.
Tel: +44 (0)1223 834800
Email: sales@magnatechled.co.uk

Global Sales and Manufacturing

Huizhou Magnatech LED

4th Floor, Building A, Tianhao Industrial Park
Zhongkai Hi-Tech Industrial Area
Huizhou City, GuangDong, China
Tel: +86 (0) 752 5707 468
Email: info@magnatechled.com