

### Optional motion sensor with multi-step dimming



Microwave motion sensor



PIR motion sensor



Zhaga Book 18 receptacle


- ◆ 5.8GHz C-band microwave or PIR
- ◆ 0-10V dimming or DALI broadcast output.
- ◆ Intelligent photocell can differentiate between natural light and LED light
- ◆ Memory function with one button commissioning.
- ◆ IR remote commissioning, easy setting and user friendly.
- ◆ Detection range up to max. 16~18m in diameter.
- ◆ Mounting height: max.12m.
- ◆ Operation temperature: -20 °C ~ + 70 °C.
- ◆ RoHS compliant.
- ◆ IP rating: IP65
- ◆ User can set daylight threshold, detection area, hold time, dim level and dim level time before off



Above daylight threshold lamp off



Below daylight threshold lamp on 100% when motion detected



After hold time lamp fades to selected dim level



After selected dim off time lamp turns off



Above daylight threshold lamp off